

# CSP-Nv Seismic Energy Source



## Key features

- Microprocessor configuration and control
- Intuitive user interface, with LCD display and LED indicators
- Enhanced operator system feedback
- Fire- Delay mode
- Flip- Flop mode
- Master / Slave Key Support
- Additional safety/protection features
- Programmable voltage technology allows operator tuning to suit application
- Remote control unit available for triggering start/stop
- High current and voltage solid state (semi-conductor) discharge method
- 'Automatic Variable Input Power' circuitry (AVIP) for reduced generator demand
- Debug log and diagnostics
- Meets EC emissions regulations enabling interference-free field use
- Supplied in robust transit case, with HV junction box (HVJ 3004) and mains lead

## CSP-Nv Overview

The CSP-Nv is built on the proven high voltage technology of the industry leading CSP range of power supplies. Incorporating microprocessor control and configuration for greater configuration flexibility and reliability whilst retaining a fail-safe logic design.

Adding to standard safety systems and operational functions found across the entire applied acoustics range of CSP energy sources, the CSP-Nv is the adaptable 'work-horse' of

the CSP range.

The CSP-Nv is available in a 1200J and 2400J version and is compatible with all of applied acoustics' Dura-Spark sound sources and Boomer systems.

# Technical Specification

## PHYSICAL

|        |   |
|--------|---|
| Size   | Transit Case (7U) with cover in place and handles flat: 50cm(H) x 58cm(W) x 74cm(D) |
| Weight | CSP-Nv 1200, case and cover: 69.4kg<br>CSP-Nv 2400, case and cover: 74.0kg          |

## ELECTRICAL SPECIFICATION

|                 |   |
|-----------------|---|
| Mains Input     | 240VAC 45-65Hz@ 5.0kVA single phase. 3 pin connector  |
| Voltage Output  | 2500 to 3950VDC, 4 pin interlocked connector<br>Solid state semi-conductor discharge method   |
| Output Energy   | Easy switch selectable in increments<br>CSP-Nv1200: 50,100,150,200,250,300,350,400,450,500,550,600<br>700,800,900,1000,1100,1200 Joules<br>CSP-Nv2400: 50,100,150,200,250,300,400,500,600,700,750,800,<br>900,1000,1250,1500,1750,2000,2250,2400 Joules |
| Charging Rate   | 2000J/second for continuous operation at 0-45°C   |
| Capacitance     | CSP-Nv 1200 208µF, 10 <sup>8</sup> shot life<br>CSP-Nv 2400 304µF, 10 <sup>8</sup> shot life  |
| Trigger         | User configured: External: +ve key (5-12VDC), -ve key or isolated closure<br>Internal: +ve key (5-12VDC), -ve key<br>Opto isolated BNC connector on front panel and remote box (optional)   |
| Repetition rate | User configured: External: 10pps maximum<br>Internal: 166ms to 60 seconds<br>Limited by charge rate, energy level and sound source rating   |
| Earth           | M8 stainless steel stud on front panel  |

## SAFETY FEATURES

|          |   |
|----------|---|
| Features | Main microprocessor control circuits with fail-safe layer of logic circuitry<br>LCD display with system status information, configuration<br>Specially designed HV connector with interlock<br>High speed dump resistors for high voltage components<br>Capacitor bleed resistors<br>HV output open circuit shutdown<br>Trigger monitoring with time out and over clock shutdown<br>HV output current monitor and shutdown<br>Supply Voltage monitoring and shutdown<br>High Voltage monitoring<br>Over temperature shutdown<br>Cover and connector interlocks<br>Diagnostic log download for improved support<br>Intelligent remote control available to configure, trigger and operate remotely |
|----------|---|

The unit's internal design has a modular construction for ease of servicing and capacitor replacement. However, for safety reasons, only applied acoustics trained engineers should attempt a repair.

## COMPATIBLE SOUND SOURCES

|                   |   |
|-------------------|---|
| <b>CSP-Nv1200</b> | AA251/AA301 boomers and S-Boom triple plate boomers; Dura-Spark L200, Dura-Spark 240/400 and Dura-Spark 400+400 |
| <b>CSP-Nv2400</b> | AA251/AA301 boomers and S-Boom triple plate boomers; Dura-Spark 240/400 and Dura-Spark 400+400                  |